



SmartBlock Relay & SSR

High Current Socketed Output Modules

HE569DQM212 (16A Form C), HE569DMQ204 (3A AC SSR), HE569DQM205 (5A DC SSR)

1 Specifications

Specifications	
General	All Versions
Outputs (Commons)	8 (8)
LED indication	ON indication per Relay Output
DC Input Power	<200mA @ 24Vdc (17-30Vdc)
Load Terminal Type	Removable Spring-Clamp (2 x 12posn)
Storage Temp.	-40° to +80° Celsius
Operating Temp.	-20° to +60° Celsius
Relative Humidity	5 to 95% Non-condensing
Dimensions HxWxD	5" x 4.31" x 2.5" (127x110x63mm)
Weight	340g (12oz.)
CE (UL) Compliance	CE (all components UL recognized)
Contact Ratings	DQM212
Contact Configuration	Normally Open & Normally Closed
AC Voltage, max.	400Vac
AC current, max.	16A*
DC Voltage, max	220Vdc
DC current, max	16A* @ 30Vdc 300mA @ 110Vdc 120mA @ 220Vdc
*at 20°C. For each 10°C ambient rise, derate max. current by 12.5%	
Minimum Output	5V @ 5mA
Response Time	8mS OFF>ON, 6mS ON>OFF
Life	30 million cycles mechanical 70,000 cycles minimum at rated load
Contact Ratings	DQM204 DQM205
Contact Configuration	Normally Open
Voltage, max.	275Vac 35Vdc
Rated Current	3A @ 240Vac 5A @ 24Vdc
Minimum Output	12Vac @ 50mA 1.5Vdc @ 1mA
Off-state leakage current	1mA 0.01mA
On-state voltage drop	1.1Vac 0.3Vdc
Response Time	OFF>ON 10mS 0.05mS
	ON>OFF 10mS 0.25mS

2 Output Wiring


Model	Top Connector Terminal Number (left to right)											
	1	2	3	4	5	6	7	8	9	10	11	12
DQM212	1C	NO	NC	2C	NO	NC	3C	NO	NC	4C	NO	NC
DQM204	1C	NO		2C	NO		3C	NO		4C	NO	
DQM205	1C	NO		2C	NO		3C	NO		4C	NO	
Model	Bottom Connector Terminal Number (left to right)											
	1	2	3	4	5	6	7	8	9	10	11	12
DQM212	5C	NO	NC	6C	NO	NC	7C	NO	NC	8C	NO	NC
DQM204	5C	NO		6C	NO		7C	NO		8C	NO	
DQM205	5C	NO		6C	NO		7C	NO		8C	NO	

C = Common NO=Normally Open NC=Normally Closed <Empty>=No Connect

2.1 CsCAN Network Wiring

Color	Signal	Description
■ Red	V+	DC Power In
□ White	CAN H	CAN Data High
	SHIELD	Shield Ground
■ Blue	CAN L	CAN Data Low
■ Black	V-	CAN Ground

2.2 CsCAN Network ID



The CsCAN Network ID is set using two 16-position rotary switches labeled HI and LO. Addresses 01-FD hex (1-253 decimal) are legal in CsCAN. To convert the readings in hex on the rotary switches to the equivalent decimal value, use the following equation:

$$ID \text{ (decimal)} = HI \times 16 + LO$$

3.0 Software Configuration

The DQM modules are configured in Cscape as a 16pt SmartStix Output module. Sixteen bits of output reference data (e.g. %Q) are assigned to the unit. The first eight bits control the relay outputs, and the last eight bits are unused.

3.1 LED Status Indication

Each output has an ON status LED physically located next to the relay on the DQM module. There is also a PWR LED (lit when DC power is applied), and CsCAN status LEDs labeled MS (module status) and NS (network status). Those LEDs are described below.


Diagnostic LED	State	Meaning
MS: (Module Status)	Solid Red	RAM or ROM test failed
	Blinking Red	I/O test failed
	Blinking Green	Module is in power-up state
NS: (Network Status)	Solid Green	Module is running normally
	Solid Red	Network Ack or Dup ID test failed
	Blinking Red	Network ID test failed
	Blinking Green	Module is in Life Expectancy default state
	Solid Green	Network is running normally

4 Installation / safety

Warning: Remove DC and AC power from the relay module and any peripheral equipment connected to this local system before adding or replacing this or any module.

- a. All applicable codes and standards should be followed in the installation of this product.

When found on the product, the following symbols specify:



5 Technical Support

North America:
Tel: 317 916-4274
Fax: 317 639-4279
Web: <http://www.heapg.com>
Email: techsppt@heapg.com

Europe:
Tel: +353-21-4321266
Fax: +353-21-4321826
Web: <http://www.horner-apg.com>
Email: tech.support@horner-apg.com

No part of this publication may be reproduced without the prior agreement and written permission of Horner APG, Inc. Information in this document is subject to change without notice.

