ABC-02 Series

USB-based configuration backup and restoration tool for managed switches and WLAN products



Features and Benefits

- One-click backup and auto-load technology to reduce system downtime
- · Powerful troubleshooting tool to record mass event logs
- Supports Moxa's managed Ethernet switches and wireless APs/bridges/ clients
- · Auto-backup of switch configuration files when any setting is changed
- Plug-and-Play system configuration backup and restoration

Certifications



Introduction

The ABC-02 Series USB automatic backup configurators are designed for Moxa's products. The ABC-02 Series can save and load configuration files, back up event logs, and load firmware via the USB interface. The ABC-02 Series makes it easier to manage the backup of system parameters and perform configurations.

Specifications

Specifications			
Interface			
Connector	USB 2.0 Type A		
Basic Operation			
Storage Capacity	1GB SLC type NAND Flash		
Power Parameters			
Input Voltage	5 VDC (through USB interface)		
Physical Characteristics			
Housing	PVC molding		
IP Rating	IP40		
Dimensions	32.5 x 97 x 12 mm (1.28 x 3.82 x 0.47 in)		
Weight	50 g (0.11 lb)		
Installation	M4 screws (<4 mm)		
Environmental Limits			
Operating Temperature	ABC-02-USB: 0 to 60°C (32 to 140°F) ABC-02-USB-T: -40 to 75°C (-40 to 167°F)		
Storage Temperature (package included)	-40 to 85°C (-40 to 185°F)		
Ambient Relative Humidity	5 to 95% (non-condensing)		



Standards and Certifications

EMC	EN 55032 Class A		
EMI	CISPR 32, FCC Part 15B Class A		
EMS	IEC 61000-4-2 ESD: Contact: 4 kV; Air: 8 kV IEC 61000-4-3 RS: 80 MHz to 1 GHz: 10 V/m		
Warranty			
Warranty Period	5 years		
Details	See www.moxa.com/warranty		
Package Contents			
Device	1 x ABC-02 Series automatic backup configurator		

Ordering Information

Documentation

Model Name	Connector	Storage	Operating Temp.
ABC-02-USB	USB 2.0 Type A	1 GB	0 to 60°C
ABC-02-USB-T	USB 2.0 Type A	1 GB	-40 to 75°C

1 x quick installation guide 1 x warranty card

© Moxa Inc. All rights reserved. Updated May 22, 2020.

This document and any portion thereof may not be reproduced or used in any manner whatsoever without the express written permission of Moxa Inc. Product specifications subject to change without notice. Visit our website for the most up-to-date product information.

